



INTERCOM - SYSTEMS

main station CP100S



The new half 19 inch main station CP100S uses the two wire principle or party line principle for full duplex operation with headsets and has a built in monitoring loudspeaker.

All headsets with dynamic microphone cartridges may be used with the station. Gooseneck microphones or wired microphones may be plugged into the 3 pin xlr connector on the units' front.

Flashing light signalization is standard and a sound alarm is switchable. When using the CP100S as a main station, a line termination switch on the reverse side must be activated. When using it as a loudspeaker station, this switch stays in OFF position.

The external power supply allows universal operation (100 - 240 V) of up to approximately 25 components. The CP100S may be mounted in a 19" rack via an optional rack kit RMK100.

Specifications

External power supply 24 VDC, 2.71 A secondary, 100-240 VAC primary provides sufficient power for up to approximately 25 intercom components.

Dimensions: 20 x 12 x 4.4 cm (w x d x h)

Weight: 785 g net without power supply

